

## DS7443S Control Station

Prod. ID

DS7443S



The DS7443S Control Station is a four-wire LED keypad with six zone LEDs. It has three programmable emergency keys for fire, special emergency, and panic.

### ■ Features

- Three programmable emergency keys
- Simple installation

### ■ Basic Functions

#### Three programmable emergency keys

The unmarked emergency key in the lower left corner of the keypad has pre-set values in the control panel as a fire emergency key. The other two keys can be programmed as a special emergency key and a panic key. Stick-on labels are provided for use if the keys are programmed.

#### Simple installation

Can be surface mounted directly to an interior wall or to a single gang box.

### ■ Planning

The recommended wiring from the control station to the control panel is 22 AWG (0.8 mm), non-shielded "telephone" quad (four-wire) cable. Although the total number of control stations allowed depends on the control panel being used, only one control station may be on any wire run. The maximum length of each wire run is also dependent on the control panel being used. Refer to the control panel's installation manual for information on total number of control stations allowed and maximum wire run length.

Note: Control station wiring cannot be shared with multiplex, options bus, telephone, or siren wiring.

### ■ Technical Specifications

|                     |                                                      |
|---------------------|------------------------------------------------------|
| Compatible Panels   | DS7400Xi, DS7080iP-32, DS7060                        |
| Enclosure           |                                                      |
| Dimensions (HxWxD): | 5 in. x 3.25 in. x 0.25 in.<br>(13 cm x 8 cm x 4 cm) |
| Power Requirements  |                                                      |
| Current Draw:       | 80 mA standby; 100 mA alarm                          |

