

RF Keyfobs

The RF3332/RF3332E and the RF3334/RF3334E are keyfobs that allow the user to arm and disarm the alarm system and send a panic alarm. The RF3332-PAN can only send a panic alarm. The keyfobs are programmed with a unique code that allows them to work only with a defined security system.

The RF3332, RF3332-PAN, and RF3334 transmit at a frequency of 304.00 MHz while the RF3332E and RF3334E transmit at 433.42 MHz.

■ Features

- Panic alarm
- Water resistance
- Maximum of 500 ft. (150 m) range

■ Approvals

FCC Compliant

Industry and Science Canada

RSS-210

■ Technical Specifications

Enclosure Design

Dimensions (H x W x D):	1.5 in. x 2.5 in. x 0.5 in. (3.8 cm x 6.3 cm x 1.3 cm)
-------------------------	---

Environmental Considerations

Operating Temperature:	-20°F to +150°F (-29°C to +65°C) <i>For UL listed requirements, the temperature range is +32°F to +120°F (0°C to +49°C)</i>
------------------------	---

Relative Humidity:	0% to 95% (non-condensing)
--------------------	----------------------------

Power Requirements

Battery:	Two 3 VDC lithium coin cell batteries
Battery Life:	5+ years under normal operating conditions with recommended battery types
Recommended Battery Types:	Duracell® DL2025, Eveready® CR2025, or Panasonic® CR2025

RF3332 2-Button Keyfob (304.00 MHz)

Prod. ID	RF3332
----------	--------



The RF3332 can arm and disarm your alarm system. The keyfob has the ability to send a panic code. The LED will flash to indicate that a signal has been sent to your alarm system.

■ Features

- Arming and disarming of security systems

■ Approvals

Approvals	FCC (ESV-0407-2)
	Industry Canada

RF3332-PAN Panic Keyfob (304.00 MHz)

Prod. ID	RF3332-PAN
----------	------------



The RF3332-PAN Panic Keyfob Transmitter can send a panic code. The LED will flash to indicate that a signal has been sent to your alarm system.

RF3332E 2-Button Keyfob (433.42 MHz)

Prod. ID	RF3332E
----------	---------



The RF3332E can arm and disarm your alarm system. The keyfob has the ability to send a panic code. The LED will flash to indicate that a signal has been sent to your alarm system.

RF3334 4-Button Keyfob (304.00 MHz)

Prod. ID	RF3334
----------	--------



The RF3334 can arm and disarm your alarm system. The keyfob has the ability to send a panic code to your monitoring alarm system and to control additional devices. The LED will flash to indicate that a signal has been sent to your alarm system.

■ Features

- Arming and disarming of security systems
- Control of additional devices such as lights or garage door openers

■ Approvals

Approvals	FCC (ESV-0407-2)
	Industry Canada

RF3334E 4-Button Keyfob (433.42 MHz)

Prod. ID

RF3334E



The RF3334E can arm and disarm your alarm system. The keyfob has the ability to send a panic code to your monitoring alarm system and to control additional devices. The LED will flash to indicate that a signal has been sent to your alarm system.